

VERİ AKTARMA KOMUTLARI

0D82:0100 8900	MOV	[BX+SI],AX
0D82:0102 C7000001	MOV	WORD PTR [BX+SI],0100
0D82:0106 B80001	MOV	AX,0100
0D82:0109 A10001	MOV	AX,[0100]
0D82:010C A30001	MOV	[0100],AX
0D82:010F 8E00	MOV	ES,[BX+SI]
0D82:0111 8C00	MOV	[BX+SI],ES
0D82:0113 FF30	PUSH	[BX+SI]
0D82:0115 50	PUSH	AX
0D82:0116 06	PUSH	ES
0D82:0117 8F00	POP	[BX+SI]
0D82:0119 58	POP	AX
0D82:011A 07	POP	ES
0D82:011B 8700	XCHG	AX,[BX+SI]
0D82:011D 91	XCHG	CX,AX
0D82:011E E520	IN	AX,20
0D82:0120 ED	IN	AX,DX
0D82:0121 E720	OUT	20,AX
0D82:0123 EF	OUT	DX,AX
0D82:0124 D7	XLAT	
0D82:0125 8D00	LEA	AX,[BX+SI]
0D82:0127 C500	LDS	AX,[BX+SI]
0D82:0129 C400	LES	AX,[BX+SI]
0D82:012B 9F	LAHF	
0D82:012C 9E	SAHF	
0D82:012D 9C	PUSHF	
0D82:012E 9D	POPF	

ARİTMETİK İŞLEM KOMUTLARI

0D82:012F 0100	ADD	[BX+SI],AX
0D82:0131 81000001	ADD	WORD PTR [BX+SI],0100
0D82:0135 050001	ADD	AX,0100
0D82:0138 1100	ADC	[BX+SI],AX
0D82:013A 81100001	ADC	WORD PTR [BX+SI],0100
0D82:013E 150001	ADC	AX,0100
0D82:0141 FF00	INC	WORD PTR [BX+SI]
0D82:0143 40	INC	AX
0D82:0144 37	AAA	
0D82:0145 27	DAA	
0D82:0146 2900	SUB	[BX+SI],AX
0D82:0148 81280001	SUB	WORD PTR [BX+SI],0100
0D82:014C 2D0001	SUB	AX,0100
0D82:014F 1900	SBB	[BX+SI],AX
0D82:0151 81180001	SBB	WORD PTR [BX+SI],0100
0D82:0155 1D0001	SBB	AX,0100
0D82:0158 FF08	DEC	WORD PTR [BX+SI]
0D82:015A 48	DEC	AX
0D82:015B F718	NEG	WORD PTR [BX+SI]
0D82:015D 3900	CMP	[BX+SI],AX
0D82:015F 81380001	CMP	WORD PTR [BX+SI],0100
0D82:0163 3D0001	CMP	AX,0100

0D82:0166 3F	AAS	
0D82:0167 2F	DAS	
0D82:0168 F720	MUL	WORD PTR [BX+SI]
0D82:016A F728	IMUL	WORD PTR [BX+SI]
0D82:016C D40A	AAM	
0D82:016E F730	DIV	WORD PTR [BX+SI]
0D82:0170 F738	IDIV	WORD PTR [BX+SI]
0D82:0172 D50A	AAD	
0D82:0174 98	CBW	
0D82:0175 99	CWD	

LOJİK İŞLEM KOMUTLARI

0D82:0176 F710	NOT	WORD PTR [BX+SI]
0D82:0178 D320	SHL	WORD PTR [BX+SI],CL
0D82:017A D128	SHR	WORD PTR [BX+SI],1
0D82:017C D138	SAR	WORD PTR [BX+SI],1
0D82:017E D100	ROL	WORD PTR [BX+SI],1
0D82:0180 D108	ROR	WORD PTR [BX+SI],1
0D82:0182 D110	RCL	WORD PTR [BX+SI],1
0D82:0184 D118	RCR	WORD PTR [BX+SI],1
0D82:0186 2100	AND	[BX+SI],AX
0D82:0188 81200001	AND	WORD PTR [BX+SI],0100
0D82:018C 250001	AND	AX,0100
0D82:018F 8500	TEST	AX,[BX+SI]
0D82:0191 F7000001	TEST	WORD PTR [BX+SI],0100
0D82:0195 A90001	TEST	AX,0100
0D82:0198 0900	OR	[BX+SI],AX
0D82:019A 81080001	OR	WORD PTR [BX+SI],0100
0D82:019E 0D0001	OR	AX,0100
0D82:01A1 3100	XOR	[BX+SI],AX
0D82:01A3 81300001	XOR	WORD PTR [BX+SI],0100
0D82:01A7 350001	XOR	AX,0100

DİZİ İŞLEM KOMUTLARI

0D82:01AA F2	REPZ
0D82:01AB A5	MOVSW
0D82:01AC A7	CMPSW
0D82:01AD AF	SCASW
0D82:01AE AD	LODSW
0D82:01AF AB	STOSW

DENETİM AKTARMA KOMUTLARI

0D82:01B0 E80002	CALL	03B3
0D82:01B3 FF10	CALL	[BX+SI]
0D82:01B5 9A00030004	CALL	0400:0300
0D82:01BA FF18	CALL	FAR [BX+SI]
0D82:01BC E90002	JMP	03BF
0D82:01BF EB06	JMP	01C7
0D82:01C1 FF20	JMP	[BX+SI]
0D82:01C3 EA00030004	JMP	0400:0300
0D82:01C8 FF28	JMP	FAR [BX+SI]
0D82:01CA C3	RET	
0D82:01CB C20001	RET	0100
0D82:01CE CB	RETF	

8086 Komut Tablosu için Komut Örnekleri

0D82:01CF CA0001	RETF	0100
0D82:01D2 7406	JZ	01DA
0D82:01D4 7C06	JL	01DC
0D82:01D6 7E06	JLE	01DE
0D82:01D8 7206	JB	01E0
0D82:01DA 7606	JBE	01E2
0D82:01DC 7A06	JPE	01E4
0D82:01DE 7006	JO	01E6
0D82:01E0 7806	JS	01E8
0D82:01E2 7506	JNZ	01EA
0D82:01E4 7D06	JGE	01EC
0D82:01E6 7F06	JG	01EE
0D82:01E8 7306	JNB	01F0
0D82:01EA 7706	JA	01F2
0D82:01EC 7B06	JPO	01F4
0D82:01EE 7106	JNO	01F6
0D82:01F0 7906	JNS	01F8
0D82:01F2 E206	LOOP	01FA
0D82:01F4 E106	LOOPZ	01FC
0D82:01F6 E006	LOOPNZ	01FE
0D82:01F8 E306	JCXZ	0200
0D82:01FA CD07	INT	07
0D82:01FC CC	INT	3
0D82:01FD CE	INTO	
0D82:01FE CF	IRET	

İŞLEMÇİ DENETİM KOMUTLARI

0D82:01FF F8	CLC	
0D82:0200 F5	CMC	
0D82:0201 F9	STC	
0D82:0202 FC	CLD	
0D82:0203 FD	STD	
0D82:0204 FA	CLI	
0D82:0205 FB	STI	
0D82:0206 F4	HLT	
0D82:0207 9B	WAIT	
0D82:0208 DFFF	ESC	3F,DI
0D82:020A F0	LOCK	
0D82:020B 90	NOP	